HARDSCAPE 1 LED WITH BRACKET

2700K Warm White 3000K Pure White 4200K Cool White 15744 AZT27 15744 AZT30 15744 AZT42 15744 CO27 15744 CO30 15744 CO42 15744 CO27 15744 GRY30 15744 CO42 15744 KD27 15744 GRY30 15744 WH122 15744 WH127 15744 WH130 15744 WH142 AZT - Textured Architectural Bronze (Marine grade powder coat) BBR - Bronzed Brass C0 - Unfinished Copper GRY - Textured Gray (Marine grade powder coat) SD - Textured Gray (Marine grade powder coat) WHT - Textured White (Marine grade powder coat) SD - Textured STB Sas, Copper Plated Brass (Copper will naturally patina over time) 1 1 Integrated High Output Nichia® LED, tightly binned for color uniformity, and constant current driver 55* 2700K (-280/+0) 3000K (-200/+175) 4200K (-400/+400) / 80s CRI A 0.19 W, 0.28 VA Multiply fixer VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 84 Lm 2700K = 48 LmW 3000K = 86 lm.W 2700 K = 84 Lm 2700K = 48 LmW 3000 K = 86 lm.W 70* of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stalness steel masonry bracket and mounting screws		1-4						
15744 BBR27 15744 C020 15744 C024 15744 C024 15744 GR42 SR24 SR24 GR42 SR24	٦	2700K War	rm White	3000K	Pure White	4200K Cool White		
BBR - Bronzed Brass CO - Unfinished Copper GW Textured Gray (Marine grade powder coat) SD - Fextured Sand (Marine grade powder coat) SD - Fextured Sand (Marine grade powder coat) WHT - Textured White (Marine grade powder coat) Image: Copper Vill maturally patina over time) Image: Copper Vill Maturally patina over time over timage: Copper Vill Maturally patina over time over timanore over t		15744 BBR 15744 CO2 15744 GRY 15744 SD2	27 7 27 7	15744 E 15744 (15744 (15744 S	3BR30 2030 GRY30 5D30	15744 BBR42 15744 C042 15744 GRY42 15744 SD42	and the	
naturally patina over time) 1 1 Integrated High Output Nichia® LED, tightly binned for color uniformity, and constant current driver 55° 2700K (-280/+0) 3000K (-200/+175) 4200K (-400/+400) / 80s CRI 0.19 W, 0.28 VA Multiply fixture VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70° of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Montering Hight 0' 1' 2' 3' 4' Mod candem at 12' 8.65 1.10 0.07 0.33 0.02 0.04 0.05 0.04 0.06 0.04 0.06 0.04 0.06 0.04 0.06 0.04 0.06 0.04 0.06 0.06 0.04 0.06 0.06 0.04 0.06 0.06 0.04 0.06 0.06 0.06 0.06 0.06 0.		BBR - Bronzed Brass CO - Unfinished Copper GRY - Textured Gray (Marine grade powder coat) SD - Textured Sand (Marine grade powder coat)						
and constant current driver 55° 2700K (-280/+0) 3000K (-200/+175) 4200K (-400/+400) / 80s CRI 0.19 W, 0.28 VA Multiply fixture VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers <u>Konteng Hegit</u> 0' 1' 2' 3' 4' tor candea at 32° 0.95 0.61 0.30 0.14 0.06 WT 744								
2700K (-280/+0) 3000K (-200/+175) 4200K (-400/+400) / 80s CRI A 0.19 W, 0.28 VA Multiply fixture VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounding Height 0' 0' 1' 2' 0' 1' 2' 0' 1' 2' 0' 1' 2' 0' 1' 2' 100 condea at 20' 0.08 0' 1' 2' 0' 1' 2' 0' 1' 2' 0' 1' 2' 0' 1' 2'								
0.19 W, 0.28 VA Multiply fixture VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Munting Height 0' 1' 2' 3' 4' for currende at 12" 8.65 1.10 0.07 0.03 0.02 for currende at 24' 2.08 0.98 0.06 0.04 for currende at 24' 0.95 0.61 0.30 0.14 0.06		55°						
Multiply fixture VA by the number of fixtures used to determine size of transformer 9V-15V AC/DC with no loss in output due to constant current technology Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' toot candles at 12" 8.65 1.10 0.07 0.03 0.02 toot candles at 12" 0.95 0.61 0.30 0.04 0.06	A.	2700K (-280/+0) 3000K (-200/+175) 4200K (-400/+400) / 80s CRI						
Tested to an L-70 of 40,000 hours 2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Haight 0' 1' 2' 3' 4' tocandes at 12" 8.65 1.10 0.07 0.03 0.02 tocandes at 12" 8.65 1.00 0.07 0.03 0.02 tocandes at 36" 0.95 0.61 0.30 0.14 0.60	1 14	Multiply fixture VA by the number of fixtures used to determine						
2700K = 8.4 Lm 2700K = 44 Lm/W 3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' toot candles at 12" 8.65 1.10 0.07 0.03 0.02 toot candles at 24" 0.98 0.30 0.06 0.04 toot candles at 36" 0.95 0.61 0.30 0.14 0.06	-	9V-15V AC/E	DC with no	loss in outp	ut due to cons	tant current technology		G
3000K = 8.6 Lm 3000K = 45 Lm/W 4200K = 11.0 Lm 4200K = 58 Lm/W 70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' toot candles at 12' 8.65 1.10 0.07 0.03 0.02 foot candles at 12' 2.08 0.98 0.30 0.06 0.04 toot candles at 36' 0.95 0.61 0.30 0.14 0.06 WT744		Tested to an L-70 of 40,000 hours						
Stainless steel masonry bracket and mounting screws 15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' foot candles at 12' 8.65 1.10 0.07 0.03 0.02 foot candles at 36' 0.95 0.61 0.30 0.14 0.06	1 2 2	3000K = 8.6 Lm 3000K = 45 Lm/W						
15716 SS - 1 LED Accessory Bracket Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' Toot candles at 12" 8.65 1.10 0.07 0.03 0.02 Toot candles at 14" 2.08 0.98 0.30 0.06 0.04 Toot candles at 36" 0.95 0.61 0.30 0.14 0.06	N.B.	70" of usable #18-2, SPT-1W leads. Pro series wire connectors supplied						
Subjected to Highly Accelerated Life Testing - 3rd party reliability testing Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' for candies at 12' 8.65 1.10 0.07 0.03 0.02 for candies at 12' 0.95 0.61 0.30 0.14 0.06		Stainless steel masonry bracket and mounting screws						
Not for use with electronic transformers Mounting Height 0' 1' 2' 3' 4' foot candles at 12" 8.65 1.10 0.07 0.03 0.02 foot candles at 12" 8.65 1.00 0.07 0.03 0.02 foot candles at 24" 2.08 0.98 0.30 0.06 0.04 foot candles at 36" 0.95 0.61 0.30 0.14 0.06		15716 SS - 1 LED Accessory Bracket						
In out candes at 12" 8.65 1.10 0.07 0.03 0.02 In out candes at 12" 2.08 0.98 0.30 0.06 0.04 In out candes at 24" 2.08 0.98 0.30 0.06 0.04 In out candes at 36" 0.95 0.61 0.30 0.14 0.06								
Indiana Indiana <thindiana< th=""> <thindiana< th=""> <thi< td=""><th></th><td>Mounting Height</td><td>0' 1</td><td>' 2'</td><td>3' 4'</td><td></td><td></td><td></td></thi<></thindiana<></thindiana<>		Mounting Height	0' 1	' 2'	3' 4'			
International and the state International and the state for candide at 36° 0.95 0.61 0.30 0.14 0.06	•	foot candles at 12"						
WT744								
LandLight								A CONTRACTOR OF A CONTRACTOR O
LandLight	2							
LandLight								
			L	an	IdL	ight		

Enhance The Night

3.0" 6 CO **BBR** Z٦ E WHT SD GRY POWERED BY DESIGN PRO LED Guaranteed not to burn out for 15 years (10 commercially)

> Professional-grade LED lighting and system components, designed and engineered for optimum all-weather performance with natural lighting effects, deliver professional results.

Enhance The Night - www.landlight.ca